General

ERV-XX-V2 and ERV-XXG-V2 timer relays are used in all fields (industry, house, plant etc.) need controlls related to the time.

Usage of Device and Working Principle

Please make the connection according to the diagram. Please adjust the delaying time by the button. Energize the device. Device will count the stand by time. On(power) led gets on when the counting occurs, Out(relay) led gets on and off. During this step contact output is (NC)1.After the time is up Out(relay) led gets on constantly and contact out put gets into (NO)3. Untill it is de-energized device remains the same.

ERV-08-V2

Device will start timing and meanwhile led switches on-off. When device is timing contact out is (NC)1.When the timing finish (set time is up) relay led light is switches on and contact out is (NO)3. Device keeps stable till the power is off.

ERV-08G-V2

Device will start timing and meanwhile led switches on-off. When device is timing contact out is (NO)3.When the timing finish (set time is up) relay led light is switches on and contact out is (NC)1.Device keeps stable till the power is off.

Maintenance

Switch off the device and release from connections.clean the trunk of device with a swab. Don't use any conductor or chemical might damage the device. make sure device works after cleaning.

Warnings

Please use the device according to the manual.
Don't use the device in wet.
Include a switch and circuit breaker in the assembly.
Put the switch and circuit breaker nearby the device, operator can reach easily.
Mark the switch and circuit breaker as releasingconnection for device.

Connection diagram for ERV-XX-V2/ERV-XXG-V2



ERV-XX-V2 (On delay)



ERV-XXG-V2 (Off delay)



Tecnical Specifications:

Operating Voltage(Un).....	: 150V-260V AC 24V DC
Operating Frequency.....	: 50/60 Hz.
Operating Power.....	: <4VA
Operating Temperature...	: -20°C.....+55°C
Time(t).....	: 0,1sec.-60min.
Display.....	: On led and Out(RLY) led
Connection Type.....	: Terminal connection
Weight.....	: Max.90gr.
Contact.....	: 5A/250V AC (Resistive Load)
Mounting.....	: Vertical assembled in the panel or assembled on the din rail
Operating Altitude.....	: <2000meter
Cable Diameter.....	: 2.5mm²

Dimensions for ERV-XX-V2/ERV-XXG-V2



Document Number: ERV-XX/XXG-V2

CE

TIMER RELAYS ERV-XX-V2/ERV-XXG-V2 ENG

General
ERV-XX-V2 and ERV-XXG-V2 timer relays are used in all fields (industry, house, plant etc.) need controlls related to the time.

Usage of Device and Working Principle
Please make the connection according to the diagram. Please adjust the delaying time by the button. Energize the device. Device will count the stand by time. On(power) led gets on when the counting occurs, Out(relay) led gets on and off. During this step contact output is (NC)1.After the time is up Out(relay) led gets on constantly and contact out put gets into (NO)3. Untill it is de-energized device remains the same.

ERV-08-V2
Device will start timing and meanwhile led switches on-off. When device is timing contact out is (NC)1.When the timing finish (set time is up) relay led light is switches on and contact out is (NO)3. Device keeps stable till the power is off.

ERV-08G-V2
Device will start timing and meanwhile led switches on-off. When device is timing contact out is (NO)3.When the timing finish (set time is up) relay led light is switches on and contact out is (NC)1.Device keeps stable till the power is off.

Maintenance
Switch off the device and release from connections.clean the trunk of device with a swab. Don't use any conductor or chemical might damage the device. make sure device works after cleaning.

Warnings
Please use the device according to the manual.
Don't use the device in wet.
Include a switch and circuit breaker in the assembly.
Put the switch and circuit breaker nearby the device, operator can reach easily.
Mark the switch and circuit breaker as releasingconnection for device.

Connection diagram for ERV-XX-V2/ERV-XXG-V2



ERV-XX-V2 (On delay)



ERV-XXG-V2 (Off delay)



Tecnical Specifications:

Operating Voltage(Un).....	: 150V-260V AC 24V DC
Operating Frequency.....	: 50/60 Hz.
Operating Power.....	: <4VA
Operating Temperature...	: -20°C.....+55°C
Time(t).....	: 0,1sec.-60min.
Display.....	: On led and Out(RLY) led
Connection Type.....	: Terminal connection
Weight.....	: Max.90gr.
Contact.....	: 5A/250V AC (Resistive Load)
Mounting.....	: Vertical assembled in the panel or assembled on the din rail
Operating Altitude.....	: <2000meter
Cable Diameter.....	: 2.5mm²

Dimensions for ERV-XX-V2/ERV-XXG-V2



Document Number: ERV-XX/XXG-V2

CE